

# 1000A AC Clamp Meter + Phase Rotation Tester

Measurements include Resistance, Capacitance and Frequency

## Features:

- 3-3/4 Digit (3999 count) LCD with Data/Peak Hold and 40-segment bargraph
- L1, L2, L3 (R,S,T) Phase Rotation Test with LCD status indication
- Measure AC Voltage to 600V and AC Current to 1000A
- AC measurements over wide (40 to 400Hz) frequency range
- Functions include Resistance, Capacitance, and Frequency
- $\pm 1.2\%$  basic ACV accuracy
- Diode test and audible Continuity
- Clamp jaws open to 1.6" (40mm)
- Overload Protection to 1100A and 600Vrms
- Overrange and low battery indication
- Complete with test leads (3), 9V battery and carrying case



CAT III-600V

Specifications	Ranges	Max Resolution	Basic Accuracy (%rdg+digits)
AC Current:	40A, 400A, 1000A	0.01A	$\pm (2\% + 5d)$
AC Voltage:	400V, 600V	0.1V	$\pm (1.2\% + 5d)$
Phase	80V to 480V	0.1V	$\pm (1.2\% + 5d)$
Capacitance	400 $\mu$ F	1 $\mu$ F	$\pm (3\% + 5d)$
Frequency	4kHz	1Hz	$\pm (0.1\% + 1d)$
Resistance	40k $\Omega$	10 $\Omega$	$\pm (1\% + 1d)$
Continuity	Audible tone < 40 $\Omega$		
Power	9V battery		
Dimensions	9 x 3 x 1.5" (228 x 76 x 39mm)		
Weight	13oz. (370g)		

## Ordering Information:

380974 .....AC Clamp Meter + Phase Rotation Tester

