

Light Meter

Digital and Analog display of light in Foot-candles or Lux

Features:

- Wide range to 20,000 Foot-Candles or Lux with high resolution to 0.01 Fc/Lux
- Relative mode indicates change in light levels
- Peak mode capture highest reading
- Remote light sensor on 12" (305mm) coiled cable — expandable to 24" (609mm)
- Utilizes precision photo diode and color correction filter
- Cosine and color corrected measurements
- High accuracy of $\pm(5\% \text{ reading} + 0.5\% \text{FS})$
- MIN/MAX feature stores maximum and minimum readings
- Data Hold freezes reading in the display
- Large LCD display with analog bargraph
- Backlight for readings in low light levels
- Dimensions: 5.9x2.95x1.57" (150x75x40mm); Weight: 7oz (200g)
- Complete with 9V battery, light sensor with protective cover, and protective holster



Ordering Information:

LT300Light Meter